



LED žarulja GX53 CCT 10W - 120° - 975lm

Ref. H3.LED.G53.CCT

LED CCT GX53 žarulja Fumagalli nudi 10W snage i 1200 lumena, sa širokim otvorom od 120°. Podesivost tona i visoka reprodukcija boja, savršeno za zamjenu halogenih sijalica do 100W. CCT 100-240V Ø100x37mm 120°



Product data

Ugao otvaranja (°)	120
Čahura	GX53
Certifikati	CE, ROHS
Razred energetske efikasnosti	E
CRI	80-85
Dimenzije (mm) LxIxh	Ø100X37
Vozač	Unutrašnji
Efikasnost (Lm/w)	120
Faktor snage (cosφ)	0,8
Frekvencija (Hz)	50 - 60
Garancija	Prema zakonskoj garanciji: 3 godine
IP	IP20
Kelvin (K)	3000, 4000, 6500
Materijal	Aluminij
Materijalni difuzor	Polikarbonat
Raspon temperature	-30°C ~ +80°C
Nominalni Napon (V)	100 - 240V AC
Vrsta LED-a	SMD 2835
Tonalitet	CCT
Spoljna upotreba	Ne
Životni vijek (h)	25000



CHIP COB
Alta calidad

CRI>85

Product variants

Reference	Attributes
H3.LED.G53.CCT	