



LED žarulja GX53 CCT 10W - 120° - 975lm

Ref. H3.LED.G53.CCT

LED CCT GX53 žarulja Fumagalli nudi 10W snage i 1200 lumena, s širokim otvorom od 120°. Podesite nijansu i izvrsnu reprodukciju boja, savršeno za zamjenu halogenih žarulja do 100W. CCT 100-240V Ø100x37mm 120°



Product data

Kut otvora (°)	120
Čaška	GX53
Certifikati	CE, ROHS
Razred energetske učinkovitosti	E
CRI	80-85
Dimenzije (mm) LxIxh	Ø100X37
Vozač	Unutarnji
Učinkovitost (Lm/w)	120
Faktor snage (cosφ)	0,8
Frekvencija (Hz)	50 - 60
Jamstvo	Prema zakonskoj garanciji: 3 godine
IP	IP20
Kelvin (K)	3000, 4000, 6500
Materijal	Aluminij
Materijalni difuzor	Polikarbonat
Raspon temperature	-30°C ~ +80°C
Nomin tension (V)	100 - 240V AC
Vrsta LED-a	SMD 2835
Tonalitet	CCT
Vanjska upotreba	Ne
Radni vijek (h)	25000



CHIP **COB**
Alta calidad

CRI>85

Product variants

Reference

Attributes

H3.LED.G53.CCT

